

# Beta Valve

QD00582FR

## Series R solenoid coil cover



The Series R coil cover has been designed to cover RPE solenoid valve coils with faston tag electrical connection. The cover is intended to provide: visual concealment of electrical connections, protection from accidental contact with live parts during installation and maintenance as well as some protection from vertical water drips.

The Series R solenoid valve cover was originally designed to fit the coils of RPE's latching (bistable) solenoid valves, however it can also be used with 2 way normally closed and 2 way normally open solenoid valves.

**Important:** When used with normally closed or normally open types attention should be paid to the coil's maximum operating temperature and we recommend a maximum duty rating of 50% ED, with a maximum power ON time of two minutes.

Dip moulded using flame retardant material.

Material:	PDM100 FR
Colour:	Black
Appearance:	Glossy
Parts will have a hardness of 55 Shore A	
Temperature rating is 65°C	
Property:	Flame Retardant
Grade:	55 Shore A Black FR Plastisol
Application:	Dip Moulding
Colour:	Black

We advise all our customers to complete their own trials to determine fitness for purpose.

Call: 01494 459 511

Visit: [BetaValve.com](http://BetaValve.com)

Email: [sales@betavalve.com](mailto:sales@betavalve.com)

# Beta Valve